Commander Omni Fiberglass Antenna, 746-776, 8.1 dBi, N Female

Please visit us on the internet at http://www.commandertech.com

Product Description

This antenna has been designed for 700 MHz mobile radio systems typically used by public safety organizations like local police and fire departments. This center-fed collinear antenna provides consistent gain and impedance across the operating frequency band designed to meet various omnidirectional antenna requirements. Capable of handling 500 Watts of power, this antenna is suited to both receive and transmit applications.



Features/Benefits

-Triple-wrapped heavy duty fiberglsass construction assuers less tip deflection - much stronger than pultruded radomes used by competitors. Center-fed design eliminates beamswing across the band.

| | | | | | | | | - | | 70 | _ | | _ |
|---|----|-----|----|--------|---|----|------|---|----|----|--------|---|--------------|
| | ec | ากา | ca | -5 | Ю | er | el i | ш | ca | TI | o | n | S |
| - | | | | \sim | г | | - | - | | ч. | \sim | - | \mathbf{r} |

| Frequency Band | 746-806 MHz | | | | | |
|---|---|--|--|--|--|--|
| Horizontal Pattern | Omni Directional | | | | | |
| Antenna Type | Fiberglass Omni | | | | | |
| Electrical Down Tilt Option | Fixed | | | | | |
| Gain, dBi (dBd) | 8.1 (6) | | | | | |
| Frequency Range, MHz | 746-776 | | | | | |
| Connector Type | N Female | | | | | |
| Connector Location | Bottom | | | | | |
| Mounting Type | Fixed | | | | | |
| Electrical Down Tilt, deg | 0 | | | | | |
| Orientation | Upright | | | | | |
| Mounting Hardware | 46 Clamp Set | | | | | |
| Rated Wind Speed, km/h (mph) | 160 (100) | | | | | |
| VSWR | < 1.5 : 1 | | | | | |
| Vertical Beamwidth, deg | 12 | | | | | |
| Polarization | Vertical | | | | | |
| Maximum Power Input, W | 500 | | | | | |
| Lightning Protection | Direct Ground | | | | | |
| Impedance, Ohms | 50 | | | | | |
| Overall Length, m (ft) | 2.62 (8.6) | | | | | |
| Element Housing Length, m (ft) | 1.95 (6.41) | | | | | |
| Mounting Pipe Diameter, m (in) | 0.07 (2.75) | | | | | |
| Support Pipe Length, m (ft) | 0.61 (2) | | | | | |
| Weight, kg (lb) | 7.3 (16) | | | | | |
| Radiating Element Material | Copper | | | | | |
| Element Housing Material | Fiberglass | | | | | |
| Support Pipe Material | 6061-T6 Aluminum | | | | | |
| Max Wind Loading Area m ² (ft ²) | 0.079 (0.85) | | | | | |
| Survival Wind Speed, km/h (mph) | 200 (125) | | | | | |
| Bend Mom @ Rated Wind 1" Below Pop of Mt Pipe, N m (ft lbf) | 150.8 (111.2) | | | | | |
| Wind Load - Side @ Rated Wind, N (lbf) | 150.5 (33.8) | | | | | |
| Shipping Weight, kg (lb) | 13.6 (30) | | | | | |
| Packing Dimensions, HxWxD mm (in) | 3300 x 100 x 100 (129.92 x 3.94 x 3.94) | | | | | |
| Packing Dimensions, HxWxD, m (ft) | 3.3 x 0.1 x 0.1 (11.2 x 0.33 x 0.33) | | | | | |
| Shipping Mode | Common Carrier | | | | | |

Notes

All information contained in this datasheet is subject to confirmation at time of ordering



Commander Omni Fiberglass Antenna, 746-776, 8.1 dBi, N Female

Please visit us on the internet at http://www.commandertech.com

Other Documentation

